

AN APPARATUS FOR CONTROLLING A MAGNETICALLY ACTUATED POWER
SWITCHING DEVICE AND METHOD OF CONTROLLING THE SAME

5 FIELD OF THE INVENTION

The present invention relates in general to the field of electrical power distribution systems. More particularly, the present invention relates to power switching control devices as used in electrical power distribution systems.

10 BACKGROUND OF THE INVENTION

A common problem in almost any electrical power distribution system is a momentary disruption of electrical service or faults, such as might be caused by a momentary short circuit. Most of these faults are self correcting and do not require permanent fuse or circuit breaker protection because they terminate quickly. If a fuse should burn out or a circuit breaker should trip, however, the power line would be open and customers would be deprived of their electrical power. Service calls to replace fuses or reset circuit breakers would then be required, thus escalating the customer's costs.

20 A power switching device system is a fault-interrupting device used to sense current, voltage, and/or frequency variations and isolate faulted portions of distribution feeders thereby protecting power lines in an electrical power distribution system. More particularly, power switching device systems,

generally, include a power switching device and a power switching control device. The power switching device may be an electromechanical device, similar to a circuit breaker that includes a magnetic actuator or magnetic latch for opening and closing each line of a power system.

5 A magnetic actuator may a solenoid that magnetically latches when energized with the proper polarity of direct current (DC). One type of magnetic actuator is the single-coil design. To operate a single-coil magnetic actuator, the current flows in one direction for a latch (close) function and in the opposite direction for the unlatch (open) function. Each power switching
10 device has three magnetic actuators (one for each phase of AC power) and each magnetic actuator is mechanically connected to a vacuum switch. Presently, each magnetic actuator requires about 20 amps to complete a latch (close) operation and about 10 amps to release.

When a power switching control device senses a fault condition in
15 a power line, the power switching control device opens the magnetic actuator. By opening the magnetic actuator, the power switching device interrupts the power flow to the remaining portion of the distribution system, *i.e.* clears the fault from the remaining portion of the system.

If the fault has not cleared itself during a fixed time interval, then,
20 as the name suggests, the power switching control device will reclose the magnetic actuator, and if the fault condition has been cleared, power service will resume. If, however, the fault condition has not been cleared, the power switching device will again trip open the magnetic actuator after a second fixed

time interval. If, after a predetermined number of reclose operations, and the fault condition has not been cleared, the power switching control device will permanently lockout the magnetic actuator (*i.e.*, permanently open the circuit). The circuit then remains open until the system is repaired and/or the fault condition is eliminated. An exemplary power switching device for use with the present invention is the VR-3S recloser manufactured and distributed by ABB Power T&D Company, Inc., Raleigh, North Carolina.

A power switching device is operated by a power switching control device (controller). Typically, the controller is an electronic control circuit that provides the intelligence that enables a power switching device to sense overcurrents, select timing operations, and time the reclosing functions. The controller is a microprocessor-based device that includes software and hardware components for controlling the operation of the power switching device. The hardware, or physical elements, are the integrated circuits, resistors, capacitors, displays, switches, and so forth. The software is the coded instructions that the microprocessor uses to control the power switching device.

A conventional controller contains various components. For example, a power supply is typically provided in a controller and provides power to other components of the controller. A voltage regulator may also be used in a controller to provide a stabilized input signal to various components in the controller. Storage or memory may also be provided for temporarily and/or permanently storing data and/or software for the controller. For use

with a power switching device, for example, this data would include line current magnitudes and command information such as multiple time-current characteristic curves and protection setting groups. The memory can be random access memory (RAM) or read only memory (ROM) or any other type of memory. ROM is preferably electrically programmable for easy modification and is used for storing programming information. The storage can be internal to the controller or external to the controller.

A controller may also include a display for displaying information and a keyboard or other input device may be used for entering information. Indicator lamps provide status information such as power switching device open, power switching device closed, control lock out, above minimum trip, malfunction and lock in. An exemplary controller unit is the PCD2000 manufactured and distributed by ABB Power T&D Company, Inc., Raleigh, North Carolina.

Typically, a controller controls (*e.g.* opens and closes) the position of magnetic actuator in a power switching device by applying a voltage across the coils in the magnetic actuator. As such, when a certain amount of voltage is applied, the actuator will open or close, thus opening or closing an associated power line. However, such a method of opening and closing a magnetic actuator oftentimes wastes energy and does not provide the ability to control the speed at which the actuators open or close. Therefore, a need exists for power switching control device that efficiently and effectively controls a magnetic actuator in a power switching device.

BRIEF SUMMARY OF THE INVENTION

The present invention satisfies the aforementioned need by providing a power switching control device and methods for using the same to control a magnetic actuator within a power switching device using a series of modulated current pulses. In one embodiment of the present invention, the modulated current pulses are tunable and, as such, enables the control device to be compatible with multiple types of actuators each having various impedance characteristics. Also, a power switching control device in accordance with the present invention may control the speed at which the magnetic actuator opens and closes.

According to one embodiment of the present invention, a method is provided for controlling a magnetic actuator within a power switching device including a magnetic actuator having a coil and an armature. In this manner, a series of modulated current pulses is applied through the coil of the magnetic actuator in a first direction such that the actuator moves from a first position to a second position and a series of modulated current pulses is applied through the coil of the magnetic actuator in a second direction such that the actuator moves from the second position to the first position.

In one embodiment of the present invention, certain operating characteristics of a power switching device can be ascertained by analyzing the impedance of the magnetic actuator coil within the power switching device. As such, the position of the magnetic actuator may be determined within the

power switching device. Alternatively, in another embodiment of the present invention, the physical condition of the magnetic actuator coil is determined.

Additionally and in another embodiment of the present invention, a power switching device control device is provided having an improved energy management system therein. In this manner, the controller includes a voltage regulator that has the ability to switch between operating modes.

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWING

Other features of the present invention are further apparent from the following detailed description of the embodiments of the present invention taken in conjunction with the accompanying figures, of which:

FIG.1 is a simplified schematic diagram of a power switching device system including a power switching control device in accordance with the present invention and a power switching device;

FIG. 2 is a flowchart of an exemplary method of controlling a power switching device in accordance with the present invention;

FIG. 3A and 3B are block diagrams of a magnetic actuator within a power switching device in the unlatched and latched positions, respectively, in which an aspect of the present invention may be embodied;

FIG. 4 is a flowchart of an exemplary method of ascertaining certain operating characteristics of an magnetic actuator in accordance with one embodiment of the present invention;

FIG. 5A and 5B are exemplary plots useful in explaining how to determine the armature position of an magnetic actuator in accordance with one embodiment of the present invention; and

FIG. 6A and 6B are schematic circuit diagrams of an exemplary voltage regulator operating in two different modes, respectively, in accordance with the present invention.

DETAILED DESCRIPTION OF THE INVENTION

The present invention provides a power switching control device and methods for using the same to control a magnetic actuator within a power switching device. In this manner, the power switching control device, in accordance with the present invention, is adapted to provide a series of modulated current pulses to control (*e.g.* to open and close) a magnetic actuator within a power switching device. A magnetic actuator is controlled within a power switching device by using a series of modulated current pulses. In one embodiment of the present invention, the power switching control device is a recloser controller and the power switching device is a recloser.

Additionally, in one embodiment of the present invention, certain operating characteristics of a magnetic actuator can be ascertained in a power switching device by viewing the impedance of the magnetic actuator coil. In this manner, the position of an armature in a magnetic actuator can be determined. Alternatively, the physical condition of the magnetic actuator coil can be determined. Additionally, in yet another embodiment of the present

invention, the power switching control device includes a regulator having the ability to switch between a switching mode and a linear mode.

FIG. 1 is a simplified schematic diagram of a power switching device system 1 in which the present invention may be embodied. A power switching device system 1 includes a power switching device 10 and a power switching device controller 20 in accordance with the present invention. The power switching device 10 is coupled to a power line 5 (e.g., between a substation and a load), and is operated by a power switching device control device 20 such as a recloser control device . The power line 5 is a three-phase power line. The power switching device 10 comprises three poles or magnetic actuators 15. Each magnetic actuator 15 is connected to an associated wire on the power line 5, thereby being energized by an associated phase.

Power switching device controller 20 comprises storage device 30 for storing power switching device operating parameters or the like and regulator 22 (described further below with respect to FIG. 5A and 5B. Regulator 22 maintains a constant output voltage even when an input voltage fluctuates. In one embodiment of the present invention, the regulator 22 has the ability to operate in a linear mode, a switching mode or both modes simultaneously. The regulator 22 in accordance with the present invention also has the ability to deliver to a load several amps for several seconds and the ability to maintain regulation over a wide range of input voltage.

The power switching control device also includes a microprocessor or CPU 35 and at least one actuator drive circuit 45. The actuator drive

circuits 45 are each connected to and control (*e.g.* open and close) a magnetic actuator in the power switching device 10. In accordance with the present invention, the actuator drive circuits are adapted to provide a series of modulated current pulses to the magnetic actuator within the power switching device. In one embodiment of the present invention, there are three actuator drive circuits located in a recloser control device each associated with a magnetic actuator in a power switching device such as recloser. As such, each actuator drive circuit uses a pulse width modulator from CPU 35 to deliver a series of tunable modulated current pulses to the magnetic actuator (not shown) in power switching device 10, such as, for example, a recloser, to open and close the magnetic actuator.

In this manner, the current pulses may be tunable by adjusting the magnitude and duration of each pulse as to open and close the magnetic actuator. By adjusting the magnitude and duration of the current pulse delivered to the magnetic actuator, the power switching control device becomes widely compatible with a variety of actuators having difference impedance characteristics because actuators having different impedances require different current magnitudes and durations in order to open and close the actuator. In one embodiment of the present invention, the power switching control device, has a low, medium and high setting for adjusting the magnitude of the current pulses such that a variety of magnetic actuators may be controlled by the power switching control device. For example, the low setting may deliver a

current pulse of 10 amps, the medium setting 20 amps and the high setting 30 amps.

In one embodiment of the present invention, the actuator drive circuits 45 are powered by a power supply 33 that is programmable from about 150 VDC to about 250VDC, however, power supply 33 may be a direct current or alternating current supply without departing from the scope of the present invention.

FIG. 2 is a flowchart of an exemplary method of controlling a magnetic actuator within a power switching device 10, which may be a recloser, for example, in accordance with the present invention. In the method, a magnetic actuator having a coil and an armature within a power switching device is controlled by a power switching control device. In particular, an input signal is inputted at step 200 and a series of modulated current pulses are applied through the coil of the magnetic actuator in a first direction such that the actuator moves from a first position to a second position (*e.g.* open to close) at step 210. In another embodiment of the present invention, a series of modulated current pulses is applied through the coil of the magnetic actuator in a second direction such that the actuator moves from the second position to a third position at step 220. For example, the third position may be the first position. In this manner, the magnetic actuator may move from an open position (first position) to a closed position (second position) and back to the open position (first position).

Additionally, in another embodiment of the present invention, while pulsing the actuator coil with a series of modulated current pulses, a current value is measured in the coil and such a current value is compared with a threshold or regulation value. In this manner, the threshold value may represent a current value at which the actuator drive will stop delivering current pulses to the magnetic actuator. In this regard, if the current value in the coil is determined to be less than the threshold value than the actuator drive coil will continue to send current pulses to the magnetic actuator, however, if the current value is determined to be greater than or equal to the threshold value than the actuator drive circuit will cease to deliver current pulses to the magnetic actuator.

Furthermore, in yet another embodiment of the invention, the series of modulated current pulses that are applied to the actuator coil are tunable. In this manner, the amplitude and duration of the modulated current pulses are tunable, and, as such, the power switching control device may control a variety of magnetic actuators.

FIG. 3A and 3B are block diagrams of a power switching device that may be controlled in accordance with the present invention. FIG. 3A shows magnetic actuator 15 in the unlatched position, *i.e.* the armature 320 is not between the magnetic actuator coils 300. The magnetic actuator 15 is held in the unlatched position by the open-spring 330. The latching motion of a magnetic actuator is accomplished, in accordance with the present invention, by applying a series of modulated current pulses through the magnetic

actuator coils 300. As such, the current flow must be in the direction that reinforces the flux density of the permanent magnet 305. In other words, as the current flows, the coil 300 works in conjunction with the coil core (not shown) and housing (not shown) to form an electromagnet. The magnetic force of the electromagnet pulls the armature 320 toward the coil core. As the armature 320 moves toward the electromagnet, the open-spring 330 is compressed. The current flow through the coils 300 continues until the armature 320 seals *i.e.*, when the armature 320 contacts the permanent magnet 305. Then, the current flow is stopped and the armature 320 is held in place by the permanent magnet 305. The magnetic actuator then remains in the latched position, as shown in FIG. 3B, until the magnetic actuator is unlatched.

Conversely, to unlatch the magnetic actuator, current is forced through the coils 300 in the direction that repels the flux of the permanent magnet 305. In this manner, as the amplitude of the current through the coil rises, the seal strength between the armature 320 and the permanent magnet 305 is weakened. The seal eventually weakens such that the force of the open-spring 330 will break the seal. Once the armature 320 is released, the open-spring 330 will then move the armature 320 to the unlatched position.

FIG. 4 is a flow chart of method in accordance with another embodiment of the present invention. In this embodiment, a method is used to ascertain certain operating characteristics of an magnetic actuator by measuring the inductance of the magnetic actuator coil.

In accordance with this embodiment of the present invention, a series of modulated current pulses are applied to a magnetic actuator coil for a predetermined interval of time at step 400. In one embodiment of the present invention, the duration of the voltage pulse is about 230 microseconds and the voltage driving the current is about 250VDC.

Then, at step 410, a current value is measured in the magnetic actuator coil during a portion of the predetermined interval of time. In one embodiment of the present invention, the current value is measured at about 200 microseconds.

The measured current amplitude is proportional to the impedance of the magnetic actuator's coil. As such, an impedance value is then determined from the measured current value at step 420. At step 430, the measured value is then compared to a predetermined threshold impedance value. Specifically, a difference is determined between the threshold value and the measured impedance. In another embodiment of the present invention, a deviation window may be used in conjunction with the threshold value to compensate for any manufacturing inconsistencies of the components of the magnetic actuator. The deviation window may be user defined and/or programmed into the magnetic actuator without departing from the present invention

The threshold value may be user definable through software implemented in the power switching control device or may be flashed into the firmware of the controller without departing from the principles of the present

invention. In one embodiment of the present invention, the controller stores the threshold value, and then compares the threshold value to the impedance.

At step 440, the result of the comparison between the threshold impedance value and the measured impedance value (*i.e.* the difference between the threshold value and the impedance) is used to establish certain operating characteristics of the magnetic actuator. For example, in accordance with the present invention, the comparison may be used to determine whether the magnetic actuator armature is in the latched or unlatched position, or the comparison may be used to determine the physical condition of the magnetic actuator coil.

Specifically, in one embodiment of the present invention, the power switching control device determines if the magnetic actuator armature is in the latched or unlatched position without the use of a sensor, such as a pole position sensor. Alternatively, the method may be used in conjunction with such a sensor to verify whether the sensor was accurate in determining whether the magnetic actuator armature is in the latched or unlatched position.

To determine the position of the magnetic actuator armature in accordance with the present invention, a series of modulated current pulses are applied through the magnetic actuator's coil at step 400. Then, the current is measured through the coil while the current pulses are being applied through the coil at step 410. At step 420, an impedance value of the magnetic actuator coil is determined from the measured current in the coil and

compared to a threshold value. In one embodiment of the present invention, the threshold value is the impedance of coil with the armature in the unlatched position. In this manner, when the impedance of the coil with the armature in the unlatched position is compared to the threshold value, such impedances
5 will be approximately the same or within a deviation or pass/fail window that can be determined by the user. Therefore, if the impedances are equal or fall within the deviation window, it is determined that the armature is in the unlatched position.

Alternatively, if the armature is in the latched position, the
10 impedance will be larger than the impedance of the coil when the armature is in the unlatched position. In such a situation, the impedance of the coil is larger because, as illustrated in FIG. 3B, when the armature is latched, the armature is positioned below the magnetic actuator coil, and therefore the magnetic flux of the armature causes the impedance of the armature coil to be
15 larger. Therefore, if the difference between the threshold value and the impedance value is larger than the deviation window, it is determined that the armature is in the latched position.

FIGS. 5A and 5B are exemplary plots of an impedance test to determine the armature position of a magnetic actuator in accordance with one
20 embodiment of the present invention. In FIG. 5A, the magnetic actuator armature, which may be the magnetic actuator as shown in FIG. 3, is located in the latched position. As such, the slope of the current curve while the series of modulated current pulses is being applied is less than the slope of the curve

in FIG. 5B because the armature (positioned below the coil) increases the impedance of the coil thereby reducing the amount of current passing through the coil. In one embodiment of the present invention, the current measurement (t_0) is taken at about 200 microseconds and the current, for example, is measured at a value of about 3.3 amps.

FIG. 5B is also an exemplary plot of an impedance test to determine the armature position of a magnetic actuator. In this plot, however, the magnetic actuator's armature is in the unlatched position. As such, the slope of the current curve during the 230-microsecond test period is much steeper than that of the current rise in FIG. 5A because the armature (not positioned below the coil) does not increase the impedance of the coil and, as such, the amount of current passing through the coil is larger than if the armature was positioned below the coil. In one embodiment of the present invention, the current measurement (t_0) is taken at about 200 microseconds and the current, for example, is measured at a value of about 5.5 amps.

As such, the user may define the threshold impedance value to correlate to, for example, about 4 amps. Consequently, any measured current value over about 4 amps will indicate the armature is in the unlatched position and any measured current value under about 4 amps will indicate the armature is in the latched position. Such a threshold value will preferably overcome substantially any measurement variations that arise from tolerance variations caused by inconsistencies in the manufacturing processes of the components of the power switching device. The threshold value, however,

could be any value without departing from the principles of the present invention.

The present invention may be used as a stand-alone method for determining magnetic actuator positions, or it may used to complement a system having pole position sensors. In this manner, the present invention may serve to verify the results of the pole position sensors. In a situation where the present invention and pole position sensors are both used, both techniques would preferably agree on the position of each magnetic actuator or an alarm function would be activated. The use of two separate detection methods will increase the overall integrity of the power switching device system.

In another embodiment of the present invention, the physical condition of each magnetic actuator coil can be determined. As such, and in accordance with the present invention, a series of modulated current pulses is applied across the magnetic actuator's coil at step 400. Then, the current is measured through the coil while the current pulses are being applied to the coil at step 410. An impedance value is determined from the measured current value at step 420.

The impedance value is then compared to a threshold value at step 430 and based on this comparison, the physical condition of the magnetic actuator coil is determined. In this manner, the threshold value is the impedance of a coil in proper working order, *e.g.*, a properly connected and non-corroded coil. In accordance with the present invention, if the impedance

value calculated from the measured current at step 420 is larger than the threshold value, a condition exists in the coil which increases the coils impedance, *e.g.*, a break in the coil winding or corrosion in the coil winding. On the other hand, if the impedance of the coil is smaller than the threshold value, a condition exists in the coil that decreases the coil's impedance, *e.g.*, a short between the coil winding. As such, if the measured value equals the threshold value then the coil is in proper working condition.

Accordingly, in one embodiment of the present invention, if the impedance value of a coil is not within a predetermined deviation window of the threshold value then the power switching device controller may signal to an operator that such a coil is in a non-operable condition. The deviation window may be user defined and/or programmed into the power switching device controller without departing from the present invention. Consequently, by comparing the impedance of the magnetic actuator coil in accordance with the present invention, the physical condition of a magnetic actuator coil may be determined.

The present invention also provides a power switching device control device having an improved energy management system therein. In this manner, the power switching control device includes an energy management system having a voltage regulator that has the ability to operate in and switch between operating modes. In one embodiment, the regulator is a 15 VDC regulator. As such, the 15 VDC regulator may receive a 250 VDC input signal and output a 15 VDC signal, for example, such 15 VDC output signal may be

used as input for 5 VDC regulator that powers a CPU within the power switching device controller.

The regulator, in accordance with the present invention, may operate in a linear mode, a switching mode or in both modes simultaneously.

5 The regulator may, for example, change modes upon instruction from a CPU or by regulator output loading. Regulator output loading occurs when external conditions require the regulator to output more power. During regulator output loading, the regulator may not necessarily fully switch from one mode to another, but in fact may operate in both modes to meet the desired loading.

10 In linear mode, or stand alone mode, the regulator operates without control from the controller's CPU and may generate a higher output with a lower efficiency. FIG. 6A is a simplified schematic of a voltage regulator, in accordance with the present invention, operating in linear mode. In this regard, the dotted lines represent the current flow when the regulator is
15 operating in linear mode. As such, the regulation voltage for the 15VDC rail is set by the forward voltage drop of zener diode Z1. The regulated voltage will be approximately 5 volts greater than the forward voltage drop of zener diode Z1. The regulation value will be the zener diode Z1 forward voltage drop plus FET Q1's minimum gate (G) to source (S) turn-on voltage. The current path that
20 feeds zener diode Z1 is from the 250VDC rail through resistor R1. The exit path from zener diode Z1 is through resistor R2 to the Return. Resistor R1 is set to a value preferably greater than about 100K ohms and resistor R2 is about 1K ohm. Inductor L1 and diode D1 act as conductors. The voltage on

the drain (D) of FET Q1 is about the same as the voltage on the 250VDC rail. The amount of current that is allowed to flow through FET Q1 and into the 15VDC rail is controlled by the voltage drop between FET Q1's gate (G) and FET Q1's source (S). When the voltage on the 15VDC rail rises, the voltage
5 difference between the gate and source will become less. The gate voltage will remain constant. When this voltage difference becomes less than about 5 volts, the current flow through FET Q1 will be decreased.

In switching mode, however, the regulator operates with a greater efficiency than in linear mode. FIG. 6B is a simplified schematic of a voltage
10 regulator, in accordance with the present invention, operating in switching mode. As such, the dotted lines represent the current-flow through the regulator while operating in switching mode. First, the CPU through PWM1 pulses FET Q1's gate. A pulse into the gate of FET Q1 will cause FET Q1 to conduct for duration of the pulse. During this duration, current starts to flow
15 through inductor L1; then the pulse's falling edge switches off FET Q1 and the current flows through inductor L1. The current pulse through inductor L1 causes inductor L1 to "ring" or oscillate. These oscillations are rectified through diode D1 and diode D2 into the 15VDC rail. Capacitor C3 blocks the 250VDC rail, allowing only the AC component of the oscillations to be rectified.
20 The pulse width of PWM 1 is narrow, so the oscillations of inductor L1 have low amplitudes. The low amplitudes reduce noise radiation into the surrounding circuits (not shown). Diode D1 helps to prevent the damping of the oscillations by blocking FET Q1's internal capacitance, and blocks the

conductive path of FET Q1's parasitic diode. Inductor L1's oscillations are very narrow; therefore one desirable characteristic of diode D1 and diode D2 is that they have a fast reverse recovery time (e.g., less than 35 nanoseconds). The voltage on the 15VDC rail is digitized by analog to digital converter 12 and the value passed to the CPU. The CPU uses the digitized voltage values of the 15VDC and 250VDC rails to determine whether PWM1 should be switched on or off. These digitized values are also used to adjust both the duration and frequency of PWM1's pulses. The regulation voltage in switching mode, for example, may be set by the power switching device control device's firmware to about 15VDC. This is about 3 volts higher than when in linear mode. Therefore, when in switching-mode FET Q1 is biased off except when pulsed by PWM1.

There are, however, situations where the CPU cannot control the voltage regulation function *i.e.* operate in switching mode. For example, the CPU cannot regulate voltage prior to being powered on or when temporarily malfunctioning. In these situations, the regulator operates in the less efficient linear or stand alone mode to regulate the voltage and then may switch to switching mode.

Additionally, the regulator, in accordance with the present invention, may switch from switching mode to linear mode or vice versa if circuitry downstream from the regulator requires more current due to an unexpected voltage dip, for example. In this manner, for example, the regulator may be operating in switching mode and, may temporarily switch to

linear mode, and as such, may dissipate a larger burst of regulated power in order to compensate for the downstream voltage dip. For example, a regulator, in accordance with the present invention, may output 0.4 amps. The regulator load, however, may temporarily require 0.8 amps and, as such, the regulator would desirably operate in linear mode and switching mode until a balanced is reached whereby the regulator delivers the power needed.

In this regard, the regulator has the ability to regulate as much power as the regulator can thermally dissipate while regulating the power. In one embodiment, the thermal energy that is dissipated will vary according to the voltage difference between a voltage source, the regulated voltage and the amount of current passing through the regulator. As such, the power dissipated (wattage) is the voltage drop between the source voltage and the regulated voltage times the current flowing through the regulator or ($P=E*I$).

As such, the regulator may operate in switching mode during normal operation, however, has the ability to switch to linear mode and supply additional power when needed. Consequently, by having the ability to switch between modes, the regulator may provide additional power, when desirable, then switch to a more efficient mode when additional power is not needed. For example, in one embodiment of the present invention, a power switching device control device, with a regulator operating in linear mode, uses about 0.2 amps from the regulator with a source voltage of about 250 VDC and a regulated voltage of about 12 VDC. Therefore, using the equation above, the power is about 47.6 watts and represents the amount of wasted heat energy. On the

other hand, with a regulator in switching mode, the power switching device control device uses 0.2 amps at 15 VDC, and using the equation above, the power loss is 4 watts.

Additionally, according to aspects of the present invention, the regulator may operate in both modes simultaneously when switching from one mode to another. In this manner, if the regulator is transitioning from one mode to another, the regulated output power will be derived from both modes of operations. Alternatively, in one embodiment of the present invention, if more downstream current is needed, the regulator, while operating in switching mode, may partially operate in linear to provide the needed current downstream. For example, if the regulator is set to regulate 12 VDC in linear mode and 15 VDC in switching mode and the desired output voltage is 13 VDC, most of the power will be derived from linear mode while a portion will be derived from switching mode. In yet another embodiment of the present invention, even while operating at 15 VDC in full switching mode, the regulator may still derive a portion of the output current from linear mode.

Portions of the invention may be embodied in the form of appropriate computer software, or in the form of appropriate hardware or a combination of appropriate hardware and software without departing from the spirit and scope of the present invention. Further details regarding such hardware and/or software should be apparent to the relevant general public. Accordingly, further descriptions of such hardware and/or software herein are not believed to be necessary.

Although illustrated and described herein with reference to certain specific embodiments, the present invention is nevertheless not intended to be limited to the details shown. Rather, various modifications may be made in the details within the scope and range of equivalents of the claims and without
5 departing from the invention.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217